


**BOSCH**

Invented for life

# D7050 Series Addressable Photoelectric Smoke and Smoke Heat Detector Heads



- ▶ Connects to the multiplex bus of the FPD-7024 or D7024 Addressable FACP and the DS7400Xi Control Panel
- ▶ Superior dust immunity
- ▶ Exclusive Chamber Check self-diagnostics
- ▶ Automatic sensitivity test features
- ▶ Easy disassembly for cleaning

The D7050 Photoelectric Smoke and Smoke Heat Detector Heads are UL Listed, open-area photoelectric smoke detectors designed for use with commercial fire protective signaling systems and household fire warning systems (see NFPA 72, the National Fire Alarm Code). They are compatible with the FPD-7024 or D7024 Addressable Fire Alarm Control Panels (FACPs) and the DS7400Xi Control Panel.

They detect large smoke particles by scattering light from a pulsed infrared source operating with a gated, high-speed, photodiode infrared sensor. The symmetry of the optical chamber allows 360° uniform smoke entry, but minimizes external light entry.

Use both of these smoke detectors for detection circuits installed in areas where personnel are present. The D7050TH has an added fixed-temperature sensor. This expands the detector application to confined areas where a fire increases air temperature slowly and where there is a substantial increase in air temperature before the fire breaks confinement, such as furnace rooms, closets, and other confined areas.

## Functions

### Detector Head and Base System

The D7050 Photoelectric Smoke and Smoke Heat Detector Heads are part of a compound system of detector head and base. The detector base installs over a back box and contains all the wiring. The detector head attaches to the base by aligning the head with the base and turning it clockwise. No tools are required for installation other than the hex key used to tighten the tamper screw. Each detector head requires a D7050-B6 detector base.

### Chamber Check Self-diagnostics

The detector meets NFPA guidelines for sensitivity testing, because you can visually inspect the detector and check the flash rate of the LED. If the calibration is out of factory-listed range, the LED on the detector double flashes once every 3 sec to 8 sec. Follow the instructions provided with the detector to clean it. The detector also sends a dirty chamber report to the control panel.

### LED Operation

When the detector is operating normally, the LED flashes once every 3 sec to 8 sec. In alarm, the detector flashes at least once per second.

### Magnetic Test Feature

Test the detector's operation by placing the SMK-TM Test Magnet next to the detector's LED for three consecutive flashes. This causes the detector to send an alarm.

## Certifications and Approvals

Region	Certification	
Europe	CE	89/336/EEC, EN55022: 1998, EN50130-4: 1995, EN60950: 2000, EN61000-3-2, EN61000-3-3, EN61000-4-2, EN61000-4-3, EN61000-4-4, EN61000-4-5, EN61000-4-6, EN61000-4-11
USA	UL	UROX: Smoke - Automatic Fire Detectors (UL268 and A), UROX7: Smoke - Automatic Fire Detectors Certified for Canada (cULus)
	FM	
	CSFM	7272-1615: 175
	NYC-MEA	12-92-E, Vol. 14
Hong Kong	HKFSD	

## Installation/Configuration Notes

### Compatible Products

The following products are compatible with the D7050 Smoke Detector and the D7050TH Smoke Heat Detector:

Category	Product ID	Product Description
Control Panels	FPD-7024	FACP
	D7024	FACP
	D7024-EXP	FACP for export
Detector Bases	D7050-B6	Two-wire base
Remote Annunciators	DRA-12/24	12/24 VDC remote annunciator
Interface Modules	D8125MUX	Multiplex bus interface module

## Parts Included

Quant.	Component
1	Detector head
1	Literature pack

## Technical Specifications

### Environmental Considerations

Radio Frequency Interference (RFI) Immunity:	No alarm or setup on critical frequencies in the range of 26 MHz to 950 MHz for field strengths less than 50 V/m
Temperature (normal operating):	+32°F to +100°F (0°C to +38°C)

**Note:** The environment where these detectors are installed must be within the specified normal operating temperature limits.

### Mechanical Properties

Color:	Off-white
Dimensions (diameter x D):	4 in. x 1.3 in. (10.2 cm x 3.3 cm)
Material:	High-impact, fire-retardant ABS plastic

### Power Requirements

Current (alarm):	0.55 mA maximum
Current (standby):	0.55 mA nominal
Power-up Time:	22 sec maximum
Voltage (minimum):	8 VDC peak from the multiplex bus

### Trademarks

Trademark names are used throughout this document. In most cases, these designations are claimed as trademarks or registered trademarks in one or more countries by their respective owners. Rather than placing a trademark symbol in every occurrence of a trademark name, Bosch Security Systems, Inc. uses the names only in an editorial fashion and to the benefit of the trademark owner with no intention of infringing the trademark.

Chamber Check is a registered trademark of Bosch Security Systems, Inc. in the United States.

## Ordering Information

### D7050 Addressable Photoelectric Smoke Detector Head

Two-wire, UL Listed, open-area smoke detector head for use with the FPD-7024 or D7024 Addressable Fire Alarm Control Panels and DS7400Xi Control Panel; requires a D7050-B6 base.

### D7050TH Addressable Photoelectric Smoke and Heat Detector Head

Two-wire, UL Listed, open-area smoke detector head with a 135°F (57°C) fixed temperature heat sensor for use with the FPD-7024 or D7024 Addressable Fire Alarm Control Panels and DS7400Xi Control Panel; requires a D7050-B6 base.

### Accessories

#### DRA-12/24 Remote Annunciator (12/24 VDC)

Designed to provide remote annunciation of alarms when connected to the D7050-B6 Multiplex Detector Base

#### DT-2 Detector Removal Tool

Use the DT-2 to remove, replace, or test the detector head

#### SMK-TM Test Magnet

Used to test detectors



**Americas:**  
Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**  
Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6258 5511  
Fax: +65 6571 2698  
apr.securitysystems@bosch.com  
www.boschsecurity.com

**Represented by**